

### WB3000 Series

#### Magnetic Dual Wire Wrist Strap Set

**A premium one-size-fits-all wrist strap set with a magnetic connection between the wrist band and coil cord.**

The WB3000 Series is a high quality adjustable anti static wrist strap with a 8' or 12' coil cord. The snaps are specially designed magnets which creates a superior electrical connection between the wrist band and coil cords. The magnet snaps eliminate the intermittent failures and wear and tear of traditional snap and spring connections.

The soft, blue woven fabric wrist band allows the skin to breathe and makes it very comfortable to wear. The band uses hypoallergenic silver-plated nylon thread for conductivity and a non-allergenic stainless steel base plate for excellent skin contact. The black coil cord terminates with a 3.5mm stereo plug and includes a 1 meg , molded resistor for safety.

The [WB3000 Series](#) are recommended for use with Transforming Technologies' [Resistance Ranger Constant Monitors](#) and are compatible with most manufacturers' constant monitors\*.

Meets or exceeds requirements of ANSI ESD-S20.20 and ESD-S1.1.



#### **Product Specifications**

##### Wrist Band

Fabric: Polyester with silver-plated nylon  
 Contact: Two paths, 180 degrees around wrist  
 Color: Blue  
 Snap: Two 4mm Magnetic Snaps  
 Snap Release: 1-5 pounds  
 Back Plate: Stainless Steel  
 Size: Adjustable - One Size Fits All

##### Coil Cord

Length: 8 feet, extended/12 feet, extended  
 Resistor: 1 meg ohm  
 Flex Life: > 50,000 flexes  
 Color: Black  
 Banana: 3.5mm Mono Stereo Plug  
 Snaps: Two

\*Compatibility with particular resistance monitors should be verified.

#### **Product Numbers**

<u>Item Number</u>	<u>Description</u>
WB3008	Wrist Strap Set, 8' cord, Magnetic Snap, 1meg
WB3012	Wrist Strap Set, 12' cord, Magnetic Snap, 1meg

For Use With Resistance Constant Monitors. Works with all brands monitors as well as Transforming Technologies models:

- [CM1600](#) - RangerPRO - Two Operator, Two Mats
- [CM1601](#) - RangerONE - One Operator
- [CM1602](#) - RangerTWO - One Operator, One Mat
- [CM2815](#) - RangerNET - Two Operator, Two Mats, Network Ready
- [CM2800](#) - RangerBOSS- Two Operator, Two Mats, Network Ready, Flexible Alarms

This document is prepared for our customers as a service, and is to the best of our knowledge true and accurate. However, it is understood and agreed by the users of this document that we will accept no liability for the conclusions reached. Users of this document may therefore wish to perform additional testing before determining that products mentioned are suitable.